

SECTION 9. PARTS LISTS.

NOTE: ALL OF THE BELOW SPECIFICATIONS AND PART NUMBERS ARE SUBJECT TO CHANGE WITHOUT NOTICE BECAUSE OF DESIGN IMPROVEMENTS OR BECAUSE OF THE AVAILABILITY OF PARTS.

B101 BLOWER: 230 VAC, 50/60 HZ SQUIRREL CAGE.....DAYTON 2C915A

CAPACITORS.....

C1A	MICA, 620 PF, 500 VDC.....	ARCO DM15621J
C1B	MICA, 200 PF, 500 VDC.....	ARCO DM15201J
C2A	MICA, 620 PF, 500 VDC.....	ARCO DM15621J
C2B	MICA, 200 PF, 500 VDC.....	ARCO DM15201J
C3A-C4B	MICA, 220 PF, 500 VDC.....	ARCO DM15221J
C5A-C6B	MICA, 110 PF, 500 VDC.....	ARCO DM15111J
C7A	MICA, 75 PF, 500 VDC.....	ARCO DM15750J
C7B	MICA, 82 PF, 500 VDC.....	ARCO DM15820J
C8A	MICA, 75 PF, 500 VDC.....	ARCO DM15750J
C8B	MICA, 82 PF, 500 VDC.....	ARCO DM15820J
C9A-C9B	MICA, 50 PF, 500 VDC.....	ARCO DM15500J
C9C	MICA, 220 PF, 500 VDC (5K).....	ARCO DM15221J
C10A	MICA, 100 PF, 500 VDC.....	ARCO DM15101J
C10B	MICA, 20 PF, 500 VDC.....	ARCO DM15200J
C10C	MICA, 22 PF, 500 VDC (5K).....	ARCO DM15220J
C10D	MICA, 160 PF, 500 VDC (5K).....	ARCO DM15161J
C11-C12	CERAMIC DISC, .0047 MF, 10 KV.....	K.D 1000120Z4722
C13 x 8	CERAMIC TRANSMITTING, 1000 PF, 5 KV.....	HE HT58T102MA
C16A	CERAMIC DISC, .01 MF, 1 KVDC.....	CENTRALAB DD104
C16B	CERAMIC DISC, .01 MF, 1 KVDC (5K).....	CENTRALAB DD104
C17	CERAMIC TRANSMITTING, 25 PF, 7.5 KV.....	HE HT50V250KA
C18 x 3	CERAMIC TRANSMITTING, 75 PF, 7.5 KV.....	HE HT50V750KA
C19 x 7	CERAMIC TRANSMITTING, 100 PF, 7.5 KV.....	HE HT50V101KA
C24	CERAMIC TRANSMITTING, 25 PF, 15 KV (5K).....	HE HT57V250KA
C30-C31	MICA, 470 PF, 500 VDC.....	ARCO DM15-471J
C33-C36	CERAMIC FEEDTHROUGH, 2000 PF, 500 VDC.....	TUSONIX 202M
C37	VARIABLE AIR TYPE, 350 PF, LOAD CONTROL.....	CARDWELL 154-10
C38-C49	CERAMIC DISC, .01 MF, 600 VDC.....	CENTRALAB DD6-103
C101-C102	OIL FILLED, .01 MF, 7.5 KV.....	PLASTIC CAP. LK80-104
C103	OIL FILLED, 16 MF, 8 KV.....	AERVOX BX0015D0008A
C104	ELECTROLYTIC, 470 MF, 50 VDC.....	ARCO ME-470-50
C105	CERAMIC DISC, .05 MF, 16 VDC.....	CENTRALAB UK16-503
C106	OIL FILLED, .01 MF, 7.5 KV (50 HZ ONLY)...	PLASTIC CAP. LK80-104
C107	CERAMIC DISC, .05 MF, 16 VDC.....	CENTRALAB UK16-503
C108-C109	CERAMIC DISC, .01 MF, 600 VDC.....	CENTRALAB DD106-103

CB101 CIRCUIT BREAKER: 30 AMPS, 250 VAC (3K).....F & B W92X11-2-30

CB102 CIRCUIT BREAKER: 40 AMPS, 250 VAC (5K).....F & B W92X11-2-40

CONNECTORS-----

J1 (3K)	HIGH VOLTAGE SOCKET AND PLUG.....	MILLEN 37501
J1 (5K)	HIGH VOLTAGE SOCKET AND PLUG.....	HENRY
J2	RF INPUT, BNC TYPE COAX CONNECTOR.....	AMPHENOL UG647/U
J3	HARNESS CONNECTOR, 8 PIN SOCKET.....	AMPHENOL 78S8
J4	RF OUT, UHF TYPE COAX CONNETOR (3K ONLY).....	AMPHENOL S0239