

J5 RELAY CONTROL, RCA TYPE PHONO JACK.....SWITCHCRAFT 3501FP
 J6 ALC FEEDBACK, RCA TYPE PHONO JACK.....SWITCHCRAFT 3501FP
 J7 FILAMENT CONNECTOR, 4 PIN JONES PLUG.....CINCH P404AB
 J8 RF OUT, N TYPE COAX CONNECTOR (5K ONLY).....AMPHENOL UG58A/U
 J101 AC INPUT, 6 PIN JONES PLUG.....CINCH P404AB
 J102 HARNESS CONNECTOR, 8 PIN PLUG.....AMPHENOL 86CP8
 J103 FILAMENT CONNECTOR, 4 PIN JONES SOCKET.....CINCH S404CCT
 J105 AC INPUT, 6 PIN JONES SOCKET.....CINCH S404CCT

DIODES-----

D1A (3K) BIASING DIODE, 10 VDC, 1.2 AMPS.....CSDC 45XV245
 D1A (5K) BIASING DIODE, 10 VDC, 2 AMPS.....CSDC 423PD10AE1
 D2 RECTIFIER, 1 AMP, 200 PIV, ALC.....MOTOROLA 1N458
 D3 RECTIFIER, 1 AMP, 1000 PIV.....GE 509
 D101-D102 RECTIFIER, 1.2 AMP, 15 KV.....CSDC 45XV246
 D103-D104 RECTIFIER, 1 AMP, 1000 PIV.....GE 509
 D105-D106 RECTIFIER, 1 AMP, 1000 PIV (5K ONLY).....GE 509
 D107 RECTIFIER, 3 AMP, 100 PIV.....MOTOROLA 1N4720
 D108 RECTIFIER, 1 AMP, 400 PIV.....MOTOROLA 1N4004
 D109 VOLTAGE SPIKE PROTECTOR, 250 VAC.....PANASONIC ERZC20DK681

F1 FUSE: CATHODE PROTECTION, 8 AG, 1.5 AMP....LITTELFUSE 361-001.5
 FUSEHOLDER: 8 AG.....LITTELFUSE 372-001A
 F101-F102 FUSE: AC MAINS, 3 AG, 3 AMP.....LITTELFUSE 312-003
 FUSEHOLDER: 3 AG.....LITTELFUSE 342-875

KNOB BAND SWITCH, TUNE CONTROL, LOAD CONTROL.....RAYTHEON 175-1-26
 KNOB SSB/CW SWITCH.....RAYTHEON 70-7WL-26

INDUCTORS-----

L1 INPUT COIL, 3.5 MHZ.....HENRY L1 3K CLASSIC
 L2 INPUT COIL, 7.0 MHZ.....HENRY L2 3K CLASSIC
 L3 INPUT COIL, 14.0 MHZ.....HENRY L3 3K CLASSIC
 L4 INPUT COIL, 21.0 MHZ.....HENRY L4 3K CLASSIC
 L5A INPUT COIL, 28.0 MHZ (3K ONLY).....HENRY L5 3K CLASSIC
 L5B INPUT COIL, 28.0 MHZ (5K ONLY).....HENRY L5 5K CLASSIC
 L6 HIGH VOLTAGE RF PLATE CHOKE.....HENRY L6 3K CLASSIC
 L7A-L7B PARASITIC SUPPRESSOR COIL.....HENRY L7 3K CLASSIC
 L8 10 METER RF OUTPUT COIL (EXPORT MODELS).....HENRY L8 3K CLASSIC
 L9 VARIABLE ROTARY INDUCTOR, LOAD CONTROL.....HENRY L9 3K CLASSIC
 L10 L-SECTION TAPPED COIL.....B & W 1608-002
 L11 RF ANTENNA CHOKE, 2.5 MH, 150 MA.....MILLER 4555
 L13 FILAMENT CHOKE, TOROID.....HENRY L13 3K CLASSIC
 L14 FILAMENT CENTERTAP CHOKE (5K only).....MILLER 6302
 L101 RESONATING FILTER CHOKE, 8 H, 800 MA.....ECA 5020

M101 METER: PLATE CURRENT, 0 TO 1 AMP.....BEEDE 913105
 M102 METER: MULTIMETER, 0 TO 1 MA.....BEEDE 913104

PILOT LIGHTS-----

PL101-PL102 TUNE AND LOAD DIAL LAMP (3K).....SYLVANIA 1829
 LIGHT HOLDER ASSEMBLY.....SMITH 1931
 PL103-PL104 STANDBY AND POWER LIGHT (3K).....SYLVANIA 327
 LIGHT HOLDER ASSEMBLY.....COMPULITE 621-1-B
 PL105-PL106 TUNE AND LOAD DIAL LAMP (3K).....SYLVANIA 1829